

MG984G / MG983G (Email GPRS)

Table 1: Summary of SMTP Protocol Error Codes (indicates an error replied from SMTP server)

<error>	Meaning
421	Service not available, closing transmission channel
450	Requested mail action not taken: mailbox unavailable
451	Requested action aborted: local error in processing
452	Requested action not taken: insufficient system storage
500	Syntax error, command unrecognized
501	Syntax error in parameters or arguments
502	Command not implemented
503	Bad sequence of commands
504	Command parameter not implemented
521	<domain> does not accept mail (see RFC1846)
530	Access denied
535	Authentication failed
550	Requested action not taken: mailbox unavailable
551	User not local; please try <forward-path>
552	Requested mail action aborted: exceeded storage allocation
553	Requested action not taken: mailbox name not allowed
554	Transaction failed

Table 2: Summary of Error Codes (indicates an error replied from mobile equipment or network)

<err>	Meaning
651	Unknown error
652	The SMTP server is busy, such as uploading the body or sending an email.
653	Failed to get IP address according to the domain name.
654	Network error, such as failed to activate GPRS/CSD context, failed to establish the TCP connection with the SMTP server or failed to send an email to the SMTP server, etc.
655	Unsupported authentication type
656	The connection for the SMTP server is closed by peer.
657	GPRS/CSD context is deactivated.
658	Timeout
659	No recipient for the SMTP server
660	Failed to send an email
661	Failed to open a file
662	No enough memory for the attachment
663	Failed to save the attachment
664	The input parameter is wrong
665	SSL authentication failed
666	Service not available, closing transmission channel
667	Requested mail action not taken: mailbox unavailable
668	Requested action aborted: local error in processing
669	Requested action not taken: insufficient system storage
670	Syntax error, command unrecognized
671	Syntax error in parameters or arguments
672	Command not implemented
673	Bad sequence of commands
674	Command parameter not implemented
675	<domain> does not accept mail (see RFC1846)
676	Access denied
677	Authentication failed
678	Requested action not taken: mailbox unavailable
679	User not local; please try <forward-path>
680	Requested mail action aborted: exceeded storage allocation
681	Requested action not taken: mailbox name not allowed
682	Transaction failed

MG984G/MG983G (Phone MMS)

Table 1: Summary of HTTP Protocol Error Codes (indicates an error replied from MMSC)

<error>	Meaning
400	Bad request
403	Forbidden
404	Not found
409	Conflict
411	Length required
500	Internal server error
502	Bad gate way

Table 2: Summary of Error Codes (indicates an error replied from mobile equipment or network)

<err>	Meaning
751	Unknown error
752	URL length error
753	URL error
754	Invalid proxy type
755	Proxy address error
756	Invalid parameter
758	CC recipient address full
759	BCC recipient address full
760	Attachments full
761	File error
762	No recipient
763	File not found
764	MMS busy
765	Server response failed
766	Error response of HTTP post
767	Invalid report of HTTP post
768	PDP activation failed
769	PDP deactivated
770	Socket creation failed
771	Socket connection failed
772	Socket read failed
773	Socket write failed
751	Socket closed
776	Encode data error
777	HTTP decode data error

Table3: Description of HTTP Response Code

<httprsp>	Meaning
200	OK
400	Bad request
403	Forbidden
404	Not found
409	Conflict
411	Length required
500	Internal server error
502	Bad gate way